



100x70x30mm



Option



PEÇA-DIN

DIN bar support

REF.		FC-12V	FC-24V
OUTPUT VOLTAGE	V _{DC} (DC)	+12 ±0.5	+24 ±0.5
MAXIMUM OUTPUT CURRENT	mA _{DC} (DC)	400	200
	(VA)		
MAINS CONSUMPTION	V _~ (AC)	90...265V~(50/60Hz)	
CONSUMPTION	W	6,5	
FREQUENCY	MHz	5...862	
LOSS OF PASSAGE	dB	3,5 Típico 3,8MAX	
		1 só saída - 1 sortie - 1 output - 1 só saída	
CONNECTION		"F" Connectors	
INPUTS		1	
OUTPUTS		2	
		1 output option	
DC SHORT CIRCUIT PROTECTION		Yes	
FALL DC		<0.2V@400mA	<0.2V@200mA
DIMENSION	LxWxH	100x70x30mm	



REF.		FC-LB12V2S	FC-LB12V1S
INPUTS	MHz	47 - 2200	
OUTPUTS	MHz	1 - TER: 47 - 860 1 - SAT: 950 - 2200	1 - TER+SAT: 47 - 2200
REC. ON		13/18V 0/22KHz DISEqC	
INPUT ANT.		13V _{DC} /280mA	
REC. OFF			
INPUT ANT.			
MAINS VOLTAGE	VAC	230V _~ ±10%	
INSERTION LOSS	dB	40...862 MHz = 1,5 950...2200 MHz = 2	



Power supply for use with the range of mast amplifiers TVF-900 (Pag. 09)